DATASHEET



Code: 71CSS1USBPB-W

Hartland CFX | HARTLAND CFX RANGE | USB Power Sockets


Product Image




Wiring

Wiring 13Amp Switched Single Sockets with USB Charging Outlet

Neutral ZZZ Earth ____ Live



Dimensions



Insert Type	1 gang 13A Single Pole Switched Socket with 1 USB Outlet 1x2.1A
Insert Colour	Polished Brass/White
EAN13 Barcode	5017504088859
Commodity Code	85363010
Luckins TSI	404387167
ETIM Class	EC000125
Dimensions(Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips
Minimum Wall Box Depth	35mm
Switched Poles	Single
Current Rating	13 Amp, USB 1 x 2.1A
Voltage	180/250V AC, USB = 5V
Maximum Load	13 Amp, USB = 2.1A
Mains Frequency	50/60Hz
IP Rating	IP2XD
Contact Gap Minimum	3mm
Terminal Capacity 1	3x2.5mm²
Terminal Capacity 2	3x4mm²
Terminal Capacity 3	2x6mm² Multi-Strand
Earth Terminal Capacity 1	3x2.5mm²
Earth Terminal Capacity 2	3x4mm²
Earth Terminal Capacity 3	2x6mm² Multi-Strand
Product Class 1	Must be earthed
Ambient Operating Temperature	-15°C to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS1363 BS EN 62368
Patents And Trade Marks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com | W: www.hamilton-litestat.cor

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes. This