## **DATASHEET**



Code: 79C1XLEDITB100

# Hartland CFX | HARTLAND CFX RANGE | LED Trailing/Leading Edge Push On/Off Rotary 2 Way Switching Dimmers

Product Image



	1	:	r	:			_	
v	v	ı	r	ı	r	1	( )	



#### Dimensions

Insert Type	1 gang 100W LED Trailing/Leading Edge Push On/Off Rotary 2 Way Switching Dimmer				
Insert Colour	Antique Brass				
EAN13 Barcode	5017504079680				
Commodity Code	85365015				
Luckins TSI	403372607				
ETIM Class	EC000025				
Dimensions(Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm				
Weight	200 GR				
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips				
Minimum Wall Box Depth	35mm				
Switched Poles	Single				
Current Rating	0.4A				
Voltage	230V AC				
Maximum Load	5-100W (10 LED Lamps MAX)				
Mains Frequency	50Hz				
IP Rating	IP2XD				
Terminal Capacity 1	2X1mm²				
Terminal Capacity 2	2x1.5mm²				
Earth Terminal Capacity 1	5x1mm²				
Earth Terminal Capacity 2	4X1.5mm²				
Earth Terminal Capacity 3	3X2.5mm²				
Earth Terminal Capacity 4	1X4mm² Multi-Strand				
Earth Terminal Capacity 5	1X6mm²				
Product Class 1	Face plate must be earthed				
Ambient Operating Temperature	-5°C to +40°C				
Recommended Location	Internal Use Only				

2000m

BS EN 60669-2-1

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com | **W:** www.hamilton-litestat.cor

**Maximum Installation** 

Standard/Approval
Additional Notes

Altitude

(WFR)

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes. This datasheet was generated on 27/04/2024 EXOE

Trailing Edge & Leading Edge Dimmer


### **DATASHEET**



Code: 79C1XLEDITB100

## Hartland CFX | HARTLAND CFX RANGE | LED Trailing/Leading Edge Push On/Off Rotary 2

**Way Switching Dimmers** 



**Patents And Trade Marks** 

CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445

**T:** +44 (0)1747 860088

: info@hamilton-litestat.com | W: www.hamilton-litestat.cor

(\M/FR)