## DATASHEET



2 gang 13A Double Pole Switched Socket with 2 USB

Code: 7G24SS2USBULTSS-QG

# Hartland G2 | HARTLAND G2 RANGE | USB Power Sockets

**Insert Type** 


#### Product Image



### Wiring



#### **Dimensions**



Insert Colour	Satin Steel/Quartz Grey
EAN13 Barcode	5051164002824
Commodity Code	85363010
Luckins TSI	407518496
ETIM Class	EC000125
Dimensions(Nominal)	Double: Height = 87.4mm Width = 144.4mm Depth = 4.65mm
Weight	253 GR
Fixing Hole Centres	Box Fixing = 120.6mm
Minimum Wall Box Depth	35mm
Switched Poles	Double
Current Rating	13 Amp, USB 2 x 2.4A
Voltage	180/250V AC USB = 5V
Maximum Load	13 Amp, USB = 2.4A X 2
Mains Frequency	50/60Hz
IP Rating	IP2XD
Contact Gap Minimum	3mm
Terminal Capacity 1	3x2.5mm²
Terminal Capacity 2	3x4mm²

Outlets 2x2.4A (4.8A Total)

#### Earth Terminal Capacity 1 Hamilton HARTLAND G2 **Earth Terminal Capacity 2** SS2USBX2ULT

Earth Terminal Capacity 3

2x6mm<sup>2</sup> Multi-Strand

2x6mm<sup>2</sup> Multi-Strand

**Ambient Operating** 

**Product Class 1** 

**Terminal Capacity 3** 

Must be earthed -15°C to +40°C

3x2.5mm<sup>2</sup>

3x4mm<sup>2</sup>

**Temperature Recommended Location** 

Internal Use Only

**Maximum Installation** Altitude

2000m

Standard/Approval

BS1363 BS EN 62368

Patents And Trade Marks

Hartland G2 is a Registered Trade Mark No

UK00003388376

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

## **DATASHEET**



Code: 7G24SS2USBULTSS-QG

Hartland G2 | HARTLAND G2 RANGE | USB Power Sockets