
DATASHEET

Code: 89C1X2V Sheer CFX | SHEER CFX RANGE | Inductive Leading Edge Push On/Off Rotary 2 Way Switching Dimmers

Product Image



Wiring



Dimensions

Insert Type	1 gang 200VA Inductive Leading Edge Push On/Off Rotary 2 Way Switching Dimmer		
Insert Colour	Antique Brass		
EAN13 Barcode	5017504069117		
Commodity Code	85365015		
Luckins TSI	387385228		
ETIM Class	EC000025		
Dimensions(Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 1.5mm plate + 3.0mm gasket		
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm		
Switched Poles	Single		
Current Rating	0.8 Amp		
Voltage	220/250V AC		
Maximum Load	200VA (low voltage) Min Load 25VA		
Mains Frequency	50Hz		
IP Rating IP2XD			
Contact Gap Minimum	None		
Terminal Capacity 1	city 1 2x1mm ²		
Terminal Capacity 2	2x1.5mm ²		
Earth Terminal Capacity 1	5x1mm ²		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m		
Standard/Approval	BS EN 60669-1		

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com | W: www.hamilton-litestat.com (WEB)

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes. This datasheet was generated on 20/04/2024 E&OE

Code: 89C1X2V Sheer CFX | SHEER CFX RANGE | Inductive Leading Edge Push On/Off Rotary 2 Way Switching Dimmers

Hemilton SHEER CFX 1X2V Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer		X sh On-Off Rotary Dimmer	Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE: It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.
86.0	0		Patents And Trade Marks	CFX is a Registered Trade Mark No 2398667 Trade Mark No. 2296586 Sheer CFX is a Registered Design under Reference Nos. R21 = 3020754 SS2 =3020755

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com | W: www.hamilton-litestat.com (WEB)

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes. This datasheet was generated on 20/04/2024 E&OE