DATASHEET




Code: LRX1XTSAB-ABB

Linea-Rondo CFX | LINEA-RONDO CFX RANGE | Multi-Way Touch Slave Controllers

Product Image



Wiring



Dimensions

Insert Type	1 gang Multi-Way Touch Slave Controller
Insert Colour	Antique Brass/Black
EAN13 Barcode	5017504481483
Commodity Code	85363010
Luckins TSI	391672736
ETIM Class	EC000025
Dimensions(Nominal)	Single: Height = 91.5mm Width = 91.5mm Depth = 4.0mm
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips
Minimum Wall Box Depth	35mm
Switched Poles	N/A
Current Rating	The same as Touch Master or Ceiling Dimmer
Voltage	220/250V AC
Maximum Load	The same as Touch Master
Mains Frequency	50Hz
IP Rating	IP2XD
Contact Gap Minimum	N/A
Terminal Capacity 1	2x1mm²
Terminal Capacity 2	2x1.5mm²
Earth Terminal Capacity 1	5x1mm²
Earth Terminal Capacity 2	4 x 1.5mm2
Earth Terminal Capacity 3	3 x 2.5mm2
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand
Earth Terminal Capacity 5	1 x 6mm2
Product Class 1	Face plate must be earthed
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS EN 60669-2-1

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com|**W:** www.hamilton-litestat.cor


(WFR)

DATASHEET



Code: LRX1XTSAB-ABB

Linea-Rondo CFX | LINEA-RONDO CFX RANGE | Multi-Way Touch Slave Controllers



Additional NotesTungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen

lamps- dimmers should be de-rated by 25%. When using mains voltage halogen load transformer - maximum rating is 210VA. To only be used with Touch

Master Dimmers

Patents And Trade Marks Linea is a Registered Trade Mark No 2398665 CFX is a

Registered Trade Mark No 2398667 Patent No. GB 2383375B Community Trd Mark No. 002906428 Linea-Rondo CFX is a UK Registered Design Certificate No: R21=2106349 SS2=2106350