## **DATASHEET**




Code: LRXDTRIDAB-ABB

# Linea-Rondo CFX | LINEA-RONDO CFX RANGE | Digital Television Sockets - Screened Non-Isolated/DAB Compatible

## **Product Image**



#### Wiring



I. Undo the cable clamp screw.


I. Iff up the cover of the clamp, be careful not to displace the MC gasket which is located on the cover.

Insert the conductor into the terminal slot which is located in the casing of the module.

The casing of the module cover is to ensure that conductor, covering the conductor, covering braid and cable are in the correct position as shown



### **Dimensions**



Insert Type	Non-Isolated TV+FM+SAT Triplexer 1in/3out (DAB Compatible)
Insert Colour	Black
EAN13 Barcode	5017504057053
<b>Commodity Code</b>	85367000
Luckins TSI	391678727
ETIM Class	EC000439
Dimensions(Nominal)	Single: Height = 91.5mm Width = 91.5mm Depth = 4.0mm
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips
Minimum Wall Box Depth	35mm
Switched Poles	N/A
Current Rating	n/a
IP Rating	IP2XD
Contact Gap Minimum	N/A
Earth Terminal Capacity 1	5x1mm²
Earth Terminal Capacity 2	4 x 1.5mm2
Earth Terminal Capacity 3	3 x 2.5mm2
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand
Earth Terminal Capacity 5	1 x 6mm2
Product Class 1	Must be earthed (ref BS7671 415.2.1)
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS EN 50083-2:2012/A1; 2015. BS EN 61169-2:2007. BS EN 61169-24:2009
Patents And Trade Marks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Community Trd Mark No. 002906428 Linea-Rondo CFX is a UK Registered Design

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre,

Certificate No: R21=2106349 SS2=2106350