# **DATASHEET**




Code: MOD-C11AB-B

# EuroFix | EUROFIX RANGE | Hotel Card Switch with LED Modules

### **Product Image**



## Wiring



## Dimensions

Insert Type	50X50mm Module 10A(6AX) Card Switch On/Off with
	Blue LED Locator
Insert Colour	Antique Brass/Black
EAN13 Barcode	5017504068226
<b>Commodity Code</b>	85363010
Luckins TSI	393800496
ETIM Class	EC000029
Dimensions(Nominal)	Module: Height = Width = Depth =
Weight	68 GR
Switched Poles	Single
Current Rating	10A (6AX)
Voltage	220/250V AC
Maximum Load	10 Amp (6 Amp inductive)
Mains Frequency	50Hz
IP Rating	IP2XD
Contact Gap Minimum	3mm
Terminal Capacity 1	3x1mm²
Terminal Capacity 2	2x1.5mm²
Terminal Capacity 3	1x2.5mm²
Earth Terminal Capacity 1	5x1mm²
Earth Terminal Capacity 2	4 x 1.5mm2
Earth Terminal Capacity 3	3 x 2.5mm2
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand
Earth Terminal Capacity 5	1 x 6mm2
Product Class 1	Face plate must be earthed
Ambient Operating	-5° to +40°C
Temperature	
Recommended Location	Internal Use Only
-	Internal Use Only 2000m

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

:: info(a)hamilton-litestat.com | **W**: www.hamilton-litestat.cor

(WFR

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes. This dataspeet was generated on 24/04/2024 FSOF

# **DATASHEET**



Code: MOD-C11AB-B

# EuroFix | EUROFIX RANGE | Hotel Card Switch with LED Modules

# Hemilton EUROFIX MOD-C11 50X50mm Module 10A(6AX) Card Switch On/Off with Blue LED Locator

**Additional Notes** 

Note Mains operated and extra low voltage products must not be installed in the same face plate aperture. When installing within the same back box a suitable phase barriers MUST be used to separate the two voltages. See BS 7671 Wiring regulations for further details.

**Patents And Trade Marks** 

EuroFix is a Registered Trade Mark No. 2560270

**T:** +44 (0)1747 860088

: info@hamilton-litestat.com | W: www.hamilton-litestat.cor