DATASHEET




Code: MOD-C11BL-B

EuroFix | EUROFIX RANGE | Hotel Card Switch with LED Modules

Product Image



Wiring



Dimensions

Insert Type	50X50mm Module 10A(6AX) Card Switch On/Off with Blue LED Locator
Insert Colour	Black/Black
EAN13 Barcode	5017504068264
Commodity Code	85363010
Luckins TSI	398666363
ETIM Class	EC000029
Dimensions(Nominal)	Module: Height = Width = Depth =
Weight	123 GR
Switched Poles	Single
Current Rating	10A (6AX)
Voltage	220/250V AC
Maximum Load	10 Amp (6 Amp inductive)
Mains Frequency	50Hz
IP Rating	IP2XD
Contact Gap Minimum	3mm
Terminal Capacity 1	3x1mm²
Terminal Capacity 2	2x1.5mm²
Terminal Capacity 3	1x2.5mm²
Earth Terminal Capacity 1	5x1mm²
Earth Terminal Capacity 2	4 x 1.5mm2
Earth Terminal Capacity 3	3 x 2.5mm2
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand
Earth Terminal Capacity 5	1 x 6mm2
Product Class 1	Face plate must be earthed
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS EN 60669-2-3

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre,

T: +44 (0)1747 860088

: info@hamilton-litestat.com | **W:** www.hamilton-litestat.com

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes. This

DATASHEET



Code: MOD-C11BL-B

EuroFix | EUROFIX RANGE | Hotel Card Switch with LED Modules

EUROFIX MOD-C11 50X50mm Module 10A(6AX) Card Switch On/Off with Blue LED Locator

Additional Notes

Note Mains operated and extra low voltage products must not be installed in the same face plate aperture. When installing within the same back box a suitable phase barriers MUST be used to separate the two voltages. See BS 7671 Wiring regulations for further details.

aet

Patents And Trade Marks

EuroFix is a Registered Trade Mark No. 2560270

T: +44 (0)1747 860088

: info@hamilton-litestat.com | **W:** www.hamilton-litestat.cor